March 1998

lip-Flops

M74LS373/DM74LS374 3-STATE Octal D-Type Transparent Latches and Edge-Triggered

FAIRCHILD

SEMICONDUCTOR IM

DM74LS373/DM74LS374 3-STATE Octal D-Type Transparent Latches and Edge-Triggered Flip-Flops

General Description

These 8-bit registers feature totem-pole 3-STATE outputs designed specifically for driving highly-capacitive or relatively low-impedance loads. The high-impedance state and increased high-logic level drive provide these registers with the capability of being connected directly to and driving the bus lines in a bus-organized system without need for interface or pull-up components. They are particularly attractive for implementing buffer registers, I/O ports, bidirectional bus drivers, and working registers.

The eight latches of the DM54/74LS373 are transparent D-type latches meaning that while the enable (G) is high the Q outputs will follow the data (D) inputs. When the enable is taken low the output will be latched at the level of the data that was set up.

The eight flip-flops of the DM54/74LS374 are edge-triggered D-type flip flops. On the positive transition of the clock, the Q outputs will be set to the logic states that were set up at the D inputs.

A buffered output control input can be used to place the eight outputs in either a normal logic state (high or low logic levels) or a high-impedance state. In the high-impedance state the outputs neither load nor drive the bus lines significantly.

The output control does not affect the internal operation of the latches or flip-flops. That is, the old data can be retained or new data can be entered even while the outputs are off.

Features

- Choice of 8 latches or 8 D-type flip-flops in a single package
- 3-STATE bus-driving outputs
- Full parallel-access for loading
- Buffered control inputs
- P-N-P inputs reduce D-C loading on data lines



Connection Diagrams (Continued)





Order Number DM54LS374J, DM54LS374W, DM74LS374WM or DM74LS374N See Package Number J20A, M20B, N20A or W20A

Function Tables DM54/74LS373

| Output | Enable | D | Output |
|---------|--------|---|--------|
| Control | G | | |
| L | н | Н | н |
| L | н | L | L |
| L | L | Х | Qo |
| н | X | Х | Z |

H = High Level (Steady State), L = Low Level (Steady State), X = Don't Care \uparrow = Transition from low-to-high level, Z = High Impedance State Q_0 = The level of the output before steady-state input conditions were established.

DM54/74LS374

| Output Control | Clock | D | Output |
|-------------------|-------|---|--------|
| L | ↑ | н | н |
| L | ↑ | L | L |
| L | L | Х | Qo |
| н | x | х | Z |



| Absolute | Maximum | Ratings (N | ote 1) |
|----------|---------|------------|--------|
|----------|---------|------------|--------|

| Supply Voltage | 7V |
|---------------------------|-----------------|
| Input Voltage | 7V |
| Storage Temperature Range | -65°C to +150°C |

 Operating Free Air Temperature Range

 DM54LS
 -55°C to +125°C

 DM74LS
 0°C to +70°C

Recommended Operating Conditions

| Symbol | Parameter | | | DM54LS373 | | | DM74LS373 | | |
|-----------------|------------------------------|-------------|-----|-----------|-----|------|-----------|------|----|
| | | | Min | Nom | Max | Min | Nom | Max | 1 |
| V _{cc} | Supply Voltage | | 4.5 | 5 | 5.5 | 4.75 | 5 | 5.25 | V |
| VIH | High Level Input Votage | | 2 | | | 2 | | | V |
| VIL | Low Level Input Voltage | | | | 0.7 | | | 0.8 | V |
| I _{OH} | High Level Output Current | | | | -1 | | | -2.6 | mA |
| I _{OL} | Low Level Output C | urrent | | | 12 | | | 24 | mA |
| tw | Pulse Width | Enable High | 15 | | | 15 | | | ns |
| | (Note 3) | Enable Low | 15 | | | 15 | | | 1 |
| t _{su} | Data Setup Time (Notes 2, 3) | | 5↓ | | | 5↓ | | | ns |
| t _H | Data Hold Time (No | otes 2, 3) | 20↓ | | | 20↓ | | | ns |
| T _A | Free Air Operating | Temperature | -55 | | 125 | 0 | | 70 | °C |

Note 1: The "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be guaranteed. The device should not be operated at these limits. The parametric values defined in the "Electrical Characteristics" table are not guaranteed at the absolute maximum ratings. The "Recommended Operating Conditions" table will define the conditions for actual device operation.

Note 2: The symbol (\downarrow) indicates the falling edge of the clock pulse is used for reference.

Note 3: $T_A = 25^{\circ}C$ and $V_{CC} = 5V$.

'LS373 Electrical Characteristics

over recommended operating free air temperature range (unless otherwise noted)

| Symbol | Parameter | Conditions | | Min | Typ (Note 4) | Max | Units |
|------------------|---------------------------|--|------|-----|-----------------|------|-------|
| VI | Input Clamp Voltage | V_{CC} = Min, I _I = -18 mA | | | | -1.5 | V |
| V _{он} | High Level Output Voltage | V _{CC} = Min | DM54 | 2.4 | 3.4 | | |
| | | I _{OH} = Max | | | | | V |
| | | V _{IL} = Max | DM74 | 2.4 | 3.1 | | |
| | | V _{IH} = Min | | | | | |
| V _{OL} | Low Level Output Voltage | V _{CC} = Min | DM54 | | 0.25 | 0.4 | |
| | | I _{OL} = Max | | | | | |
| | | V _{IL} = Max | DM74 | | 0.35 | 0.5 | V |
| | | V _{IH} = Min | | | | | |
| | | I _{OL} = 12 mA | DM74 | | | 0.4 | |
| | | V _{CC} = Min | | | | | |
| l _i | Input Current @ Max | V_{CC} = Max, V_{I} = 7V | | | | 0.1 | mA |
| | Input Voltage | | | | | | |
| I _{IH} | High Level Input Current | V _{CC} = Max, V _I = 2.7V | | | | 20 | μA |
| I _{IL} | Low Level Input Current | V_{CC} = Max, V_{I} = 0.4V | | | | -0.4 | mA |
| I _{ozh} | Off-State Output Current | V_{CC} = Max, V_O = 2.7V | | | | | |
| | with High Level Output | V _{IH} = Min, V _{IL} = Max | | | | 20 | μA |
| | Voltage Applied | | | | | | |
| l _{ozl} | Off-State Output Current | V_{CC} = Max, V_O = 0.4V | | | | | |
| | with Low Level Output | V _{IH} = Min, V _{IL} = Max | | | | -20 | μA |
| | Voltage Applied | | | | | | |
| l _{os} | Short Circuit | V _{CC} = Max | DM54 | -20 | | -100 | mA |
| | Output Current | (Note 5) | DM74 | -50 | | -225 | |

'LS373 Electrical Characteristics (Continued)

over recommended operating free air temperature range (unless otherwise noted) Symbol Parameter Conditions Min Тур Max Units (Note 4) V_{CC} = Max, OC = 4.5V, $I_{\rm CC}$ Supply Current 24 40 mΑ D_n , Enable = GND

'LS373 Switching Characteristics

at V_{CC} = 5V and T_A = 25°C

| | | From | | R _L = | 667 Ω | | |
|------------------|-----------------------|----------|------------------|------------------|--------------------|--------|-------|
| Symbol | Parameter | (Input) | C _L = | 45 pF | C _L = 1 | 150 pF | Units |
| | | То | Min | Max | Min | Max | |
| | | (Output) | | | | | |
| t _{PLH} | Propagation Delay | Data | | | | | |
| | Time Low to High | to | | 18 | | 26 | ns |
| | Level Output | Q | | | | | |
| t _{PHL} | Propagation Delay | Data | | | | | |
| | Time High to Low | to | | 18 | | 27 | ns |
| | Level Output | Q | | | | | |
| t _{PLH} | Propagation Delay | Enable | | | | | |
| | Time Low to High | to | | 30 | | 38 | ns |
| | Level Output | Q | | | | | |
| t _{PHL} | Propagation Delay | Enable | | | | | |
| | Time High to Low | to | | 30 | | 36 | ns |
| | Level Output | Q | | | | | |
| t _{PZH} | Output Enable | Output | | | | | |
| | Time to High | Control | | 28 | | 36 | ns |
| | Level Output | to Any Q | | | | | |
| t _{PZL} | Output Enable | Output | | | | | |
| | Time to Low | Control | | 36 | | 50 | ns |
| | Level Output | to Any Q | | | | | |
| t _{PHZ} | Output Disable | Output | | | | | |
| | Time from High | Control | | 20 | | | ns |
| | Level Output (Note 6) | to Any Q | | | | | |
| t _{PLZ} | Output Disable | Output | | | | | |
| | Time from Low | Control | | 25 | | | ns |
| | Level Output (Note 6) | to Any Q | | | | | |

Note 4: All typicals are at $V_{CC} = 5V$, $T_A = 25^{\circ}C$.

Note 5: Not more than one output should be shorted at a time, and the duration should not exceed one second. Note 6: $C_L = 5 \text{ pF}.$

Recommended Operating Conditions

DM54LS374 DM74LS374 Symbol Parameter Units Min Nom Min Nom Мах Max 4.75 5.25 $V_{\rm CC}$ Supply Voltage 4.5 5 5.5 5 V V_{IH} High Level Input Voltage 2 2 V V_{IL} Low Level Input Voltage 0.7 0.8 V High Level Output Current -1 -2.6 mΑ I_{OH} Low Level Output Current 12 24 mΑ I_{OL}

| Recommended | Operating | Conditions | (Continued) |
|-------------|-----------|------------|-------------|
|-------------|-----------|------------|-------------|

| Symbol | Parameter | | C | DM54LS374 | | DM74LS374 | | | Units |
|-----------------|------------------------------|------------|-----|-----------|-----|-----------|-----|-----|-------|
| | | | Min | Nom | Max | Min | Nom | Max | |
| t _{vv} | Pulse Width | Clock High | 15 | | | 15 | | | ns |
| | (Note 8) | Clock Low | 15 | | | 15 | | | |
| t _{su} | Data Setup Time (Notes 7, 8) | | 20↑ | | | 20↑ | | | ns |
| t _H | Data Hold Time (Notes 7, 8) | | 1↑ | | | 1↑ | | | ns |
| T _A | Free Air Operating Temperatu | ıre | -55 | | 125 | 0 | | 70 | °C |

Note 7: The symbol (\uparrow) indicates the rising edge of the clock pulse is used for reference.

Note 8: $T_A = 25^{\circ}C$ and $V_{CC} = 5V$.

'LS374 Electrical Characteristics

over recommended operating free air temperature range (unless otherwise noted)

| Symbol | Parameter | Conditions | | Min | Typ (Note 9) | Max | Units |
|------------------|---------------------------|--|--|-----|-----------------|------|-------|
| Vi | Input Clamp Voltage | $V_{\rm CC}$ = Min, I _I = -18 m | V_{CC} = Min, I _I = -18 mA | | | -1.5 | V |
| V _{он} | High Level Output Voltage | V _{CC} = Min | DM54 | 2.4 | 3.4 | | |
| | | I _{OH} = Max | DM74 | 2.4 | 3.1 | | V |
| | | V _{IL} = Max | | | | | |
| | | V _{IH} = Min | | | | | |
| V _{OL} | Low Level Output Voltage | V _{CC} = Min | DM54 | | 0.25 | 0.4 | |
| | | I _{OL} = Max | DM74 | | 0.35 | 0.5 | |
| | | V _{IL} = Max | | | | | V |
| | | V _{IH} = Min | | | | | |
| | | I _{OL} = 12 mA | DM74 | | 0.25 | 0.4 | |
| | | V _{CC} = Min | | | | | |
| l _i | Input Current @ Max | $V_{CC} = Max, V_I = 7V$ | | | | 0.1 | mA |
| | Input Voltage | | | | | | |
| I _{IH} | High Level Input Current | V_{CC} = Max, V_{I} = 2.7V | | | | 20 | μA |
| I _{IL} | Low Level Input Current | $V_{\rm CC}$ = Max, $V_{\rm I}$ = 0.4V | | | | -0.4 | mA |
| I _{OZH} | Off-State Output | $V_{\rm CC} = Max, V_{\rm O} = 2.7$ | | | | | |
| | Current with High | $V_{IH} = Min, V_{IL} = Max$ | V _{IH} = Min, V _{IL} = Max | | | 20 | μA |
| | Level Output | | | | | | |
| | Voltage Applied | | | | | | |
| l _{ozL} | Off-State Output | $V_{\rm CC}$ = Max, $V_{\rm O}$ = 0.4 | / | | | | |
| | Current with Low | $V_{IH} = Min, V_{IL} = Max$ | | | | -20 | μA |
| | Level Output | | | | | | |
| | Voltage Applied | | | | | | |
| l _{os} | Short Circuit | V _{CC} = Max | DM54 | -50 | | -225 | mA |
| | Output Current | (Note 10) | DM74 | -50 | | -225 | |
| I _{cc} | Supply Current | $V_{CC} = Max, D_n =$ GND, OC = 4.5V | | | 27 | 45 | mA |

| | | | R _L = | 667 Ω | | |
|------------------|----------------------------------|------------------|------------------|--------------------|--------|-------|
| Symbol | Parameter | C _L = | 45 pF | C _L = 7 | 150 pF | Units |
| | | Min | Max | Min | Max | |
| f _{MAX} | Maximum Clock Frequency | 35 | | 20 | | MHz |
| t _{PLH} | Propagation Delay Time | | 28 | | 32 | ns |
| | Low to High Level Output | | | | | |
| t _{PHL} | Propagation Delay Time | | 28 | | 38 | ns |
| | High to Low Level Output | | | | | |
| t _{PZH} | Output Enable Time | | 28 | | 44 | ns |
| | to High Level Output | | | | | |
| t _{PZL} | Output Enable Time | | 28 | | 44 | ns |
| | to Low Level Output | | | | | |
| t _{PHZ} | Output Disable Time | | 20 | | | ns |
| | from High Level Output (Note 11) | | | | | |
| t _{PLZ} | Output Disable Time | | 25 | | | ns |
| | from Low Level Output (Note 11) | | | | | |

Note 9: All typicals are at V_{CC} = 5V, T_A = 25°C.

Note 10: Not more than one output should be shorted at a time, and the duration should not exceed one second.

Note 11: C_L = 5 pF.





LIFE SUPPORT POLICY

wv

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DE-VICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMI-CONDUCTOR CORPORATION. As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- 2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

| | Fairchild Semiconductor | Fairchild Semiconductor | Fairchild Semiconductor | National Semiconductor |
|-----|--------------------------|-------------------------------------|-----------------------------|------------------------|
| | Corporation | Europe | Hong Kong Ltd. | Japan Ltd. |
| | Americas | Fax: +49 (0) 1 80-530 85 86 | 13th Floor, Straight Block, | Tel: 81-3-5620-6175 |
| | Customer Response Center | Email: europe.support@nsc.com | Ocean Centre, 5 Canton Rd. | Fax: 81-3-5620-6179 |
| | Tel: 1-888-522-5372 | Deutsch Tel: +49 (0) 8 141-35-0 | Tsimshatsui, Kowloon | |
| | | English Tel: +44 (0) 1 793-85-68-56 | Hong Kong | |
| | | Italy Tel: +39 (0) 2 57 5631 | Tel: +852 2737-7200 | |
| ww. | fairchildsemi.com | | Fax: +852 2314-0061 | |
| | | | | |

Fairchild does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and Fairchild reserves the right at any time without notice to change said circuitry and specifications